

EVA-2210

LoRaWAN 3-Phase Current Meter with 3 x 75A Clamp-On CT

Preliminary



Features

- LoRaWAN wireless connectivity
- 3 x 75A Clamp-On CT
- Battery life up till 3.5 years@25 °C, 60mins interval setting
- Easy to deploy and maintain

Introduction

EVA-2210 is capable to measure equipment current at different kinds of application, such like pumps, fan motors, compressors, computers, servers, etc. With its wide range, high penetration rate LoRa connectivity, the data transmission range can up till hundred or thousand meters away. EVA-2210 can be installed directly on the walls, metal box or poles. EVA-2310 is powered by 2 AA 3.6v Li-ion batteries, battery life can up till 3.5 years basing on certain condition.

Common Specification

Wireless Communication

- **Frequency Band** EU 863-870 (MHz) / US 902-928 (MHz) / AU 915-928 (MHz) / AS 919-924 (MHz)
- **Spreading Factor** 7-12
- **Transmit Power** Up to 20dBm
- **Topology** Star (LoRa/LoRaWAN)
- **Sensitivity** -148dB

General

- **Power Input** 3.6V AA Battery *2pcs (Not included)
- **Battery Life** 3.5 years@25 °C, 60mins interval setting
- **LED Indicator** Power on, TX, reset to default
- **Configuration Interface** Wireless downlink commands
- **IP Class** IP30
- **Mounting** Wall, Magnetic, Pole
- **Dimension (H x W x D)** 112 x 51 x 71.5 mm
- **Certification** CE (RED), FCC, TELEC, RCM, NCC

Environment

- **Operating Temperature** -20°C to 55 °C
- **Operating Humidity** 0% ~ 90% RH
- **Storage Temperature** -40°C ~ 85°C
- **Storage Humidity** 0% ~ 90% RH

Clamp-On CT

- **Measurement Range** 100mA to 75A
- **Ratio** 3000:1
- **Operating Temperature** -40°C ~ 85°C
- **Accuracy** <±1% (300mA to 75A)
- **Sample rate** 8kHz
- **Detection period** 3 seconds

Ordering Information

LoRaWAN 3-Phase Current Meter w/75A CT

- **EVA-2210-NA** LoRaWAN 3-Phase Current Meter w/75A CT - US 902-928 (MHz)
- **EVA-2210-EA** LoRaWAN 3-Phase Current Meter w/75A CT - EU 863-870 (MHz)
- **EVA-2210-TA** LoRaWAN 3-Phase Current Meter w/75A CT - AS 919-924 (MHz)
- **EVA-2210-ZA** LoRaWAN 3-Phase Current Meter w/75A CT - AU 915-928 (MHz)

LoRaWAN Gateway

- **WISE-6610-N100-A** LoRaWAN gateway supports up to 100 nodes with 915 MHz
- **WISE-6610-E100-A** LoRaWAN gateway supports up to 100 nodes with 868 MHz
- **WISE-6610-A100-A** LoRaWAN gateway supports up to 100 nodes with 923 MHz

Accessories

- ***1760002647-01** Bat. Cylindrical 3.6V/2500mAh AA Li/SOCI2

*One EVA sensor need 2 batteries.