

ADAM-6717

AI
8
DI
5
DO
4

Address 0X	Ch	Description	Attribute	Address 4X	Ch	Description	Attribute
00001	0	DI Value	R	40031~40032	0	AI Floating Value (IEEE754)	Read
00002	1		R	40033~40034	1		Read
00003	2		R	40035~40036	2		Read
00004	3		R	40037~40038	3		Read
00005	4		R	40039~40040	4		Read
00017	0	DO Value	R/W	40041~40042	5		Read
00018	1		R/W	40043~40044	6		Read
00019	2		R/W	40045~40046	7		Read
00020	3		R/W	40047~40048	reserve		Read
				40201	0		
00121	0	Open-Circuit Flag (Burnout)	Read	40202	1	Type Code	R/W
00122	1		Read	40203	2		R/W
00123	2		Read	40204	3		R/W
00124	3		Read	40205	4		R/W
00125	4		Read	40206	5		R/W
00126	5		Read	40207	6		R/W
00127	6		Read	40208	7		R/W
00128	7		Read	40209	reserve		Read
				40211		Module Name 1	Read
				40212		Module Name 2	Read
				40221	All	AI Channel Enable	R/W